

## Digital Clamp PCE-CM 3-ICA

### Clamp meter PCE-CM 3-ICA incl. ISO Calibration Certificate Fork Clamp Up to 200 A AC / AC / DC Voltage Measurement / Simple Current Measurement / LC display / Continuity test / Thermometer

The fork current clamp PCE-CM 3 is used for quick and easy AC measurements. For current measurement, the fork current clamp is placed over the current-carrying conductor. The PCE-CM 3 Fork Clamp is particularly suitable for the measurement of AC in distributions and wherever circuits must not be interrupted. The current measuring range extends from 0 ... 200 A. In addition to the current measurement, the fork current clamp can be used to measure DC and AC voltages up to 600V, resistances, capacitances and even temperatures. The measured values are displayed on the illuminated display of the fork current clamp.

The compact dimensions and the low weight distinguish this current clamp as well as the robust housing. This makes the PCE-CM 3 fork clamps the perfect companion for installers and service technicians.

- Digital Multimeters up to 200 A
- Compact dimensions
- Robust plastic housing
- Multimeter functions
- Battery operation
- Backlit LCD
- **Incl. ISO Calibration Certificate**

#### Specifications:

#### DC

Measuring range	Resolution	Accuracy
4V DC	1 mV	± (1.2% of measured value + 2 digits)
40V DC	10 mV	± (1.5% of measured value + 2 digits)
400V DC	100 mV	± (1.5% of measured value + 2 digits)
600V DC	1V	± (2% of measured value + 2 digits)
Input impedance	10 MΩ	
Overvoltage protection	600V DC 600V AC RMS	

#### AC

Measuring range	Resolution	Accuracy
4V AC	1 mV	± (1.5% of measured value + 5 digits)
40V AC	10 mV	± (1.5% of measured value + 2 digits)
400V AC	100 mV	± (1.5% of measured value + 2 digits)
600V AC	1V	± (2% of measured value + 2 digits)

Input impedance	10 MΩ
Overvoltage protection	600V DC 600V AC RMS
Frequency range	50 ... 400 Hz

### Alternating current

#### Measuring range

200 A AC

#### Resolution

100-mA

#### Accuracy

± (3.0% of measured value + 5 digits)

Overload protection

200 A AC

Frequency range

50 ... 60 Hz

### Resistance

#### Measuring range

400 Ω

4 kΩ

40 kΩ

400 kΩ

4 MΩ

40 MΩ

#### Resolution

0.1 Ω

1 Ω

10 Ω

100 Ω

1 kΩ

10 kΩ

#### Accuracy

± (1% of measured value + 4 digits)

± (1.5% of measured value + 4 digits)

± (1.5% of measured value + 4 digits)

± (1.5% of measured value + 4 digits)

± (2.5% of measured value + 4 digits)

± (3.5% of measured value + 4 digits)

Overvoltage protection

250V DC  
250 AC RMS

Connection thermocouple

Type K connection with adapter

### Capacity

#### Measuring range

4 nF

40 nF

400 nF

4 μF

40 μF

100 μF

#### Resolution

0.1 nF

1 nF

10 nF

100 nF

1 μF

10 μF

#### Accuracy

± (5% of measured value + 20 digits)

± (3% of measured value + 5 digits)

± (3% of measured value + 10 digits)

Overvoltage protection

250V DC  
250 AC RMS

Check feature

Diode test

Test

Test current: 0.5-mA

Reverse Voltage: 1.5V

Display

Forward voltage of the diode

Continuity test

Open circuit Voltage 0.5V

Noise when resistance <50 Ω

Overvoltage protection

250V DC  
250 AC RMS

### General technical specifications

Jaw Capacity

About 17 mm / .7 in

Display

4000 digit LCD with backlight

Continuity test

Noise when resistance <50 Ω

Test current

About 0.5-mA

Open circuit voltage

< 2V DC

Battery indicator

Battery icon when battery voltage low

Display overrange

OL appears in the display

Refresh rate display

3 Hz

Temperature sensor

Thermocouple type K

Input impedance

10 MΩ

Operating conditions	5 ... 40°C / 41 ... 104°F, 80% rh non-condensing
Storage conditions	-20 ... 60°C / -4 ... 140°F, 80% rh non-condensing
Operating altitude	< 2000 m / 6561 ft
Power supply	2 x 1.5V AAA battery
Automatic shutdown	30 minutes
Security conditions	IEC1010-1 (2001) CAT II 1000V CAT III 600V
Pollution degree	2

#### Delivery scope:

- 1 x Clamp meter PCE-CM 3
- 2 x Test leads
- 2 x Measuring tip
- 1 x Adapter thermocouple
- 1 x Thermocouple type K
- 2 x AAA batteries 1.5V
- 1 x User manual
- 1 x ISO Calibration Certificate