



深圳市宏之都科技有限公司
HONGDU TESTING EQUIPMENT CO., LTD.

HD-RL-20A Load machine



According to apple.080-4942.080-1276, the standard equipment designed for various technical requirements. It is mainly used for load energization tests of power plugs, converters, various switches and passive products between various contact conductors. The testing machine has the advantages of beautiful appearance, reasonable layout, stable and reliable performance, convenient use and maintenance. Can be used in conjunction with our related equipment to provide the required load for testing.

Technical Parameters:

Serial number	Project	Specifications
1	Maximum input current	AC 70A
2	The output voltage	AC 0-290V Adjustable
3	Output current	AC 0-20A Adjustable / per station
4	Voltage accuracy	$\pm (0.4\% \text{ reading} + 0.1\% \text{ range} + 1 \text{ word})$

5	Current accuracy	$\pm (0.4\% \text{ reading} + 0.1\% \text{ range} + 1 \text{ word})$
6	Hold time	0~30H can be set
7	Input power	AC 220V \pm 10% , 50Hz/60Hz
8	Protective function	Voltage and current are digital display, with leakage protection